



CONTROL BOX

- 1 - POWER SWITCH - 10A @ 230V, 2-POLE (ESW-130)
- 2 - POWER RELAY - DPDT, 30A, 240VAC (ERL-030)
- 3 -
- 4 - UNIT COOLER - 1.2A, 220V, 50/60Hz (RCO-084)
- 5 - POWER CORD - 3-WIRE, 25A, 230VAC (ECD-021)
- 6 - CONDENSING UNIT - 230/1/50, 5.7A (RCU-057)
- 7 - CONTROLLER W/ OVERLAY - 85-264VAC, 50/60Hz (ETC-108 & ETC-109)
- 8 - TEMPERATURE SENSOR - RTD, 100 Ohm, 0.00385 Ohm/Ohm/°C (ETC-052)
- 9 - RELAY - NO, 3-32VDC INPUT, 24-240VAC, 25A (ERL-039)
- 10 - HEATER - 250W @ 230VAC, 1.1A (EHE-046)
- 11 -
- 12 - SOLENOID VALVE - 3/8" LINE, 240VAC/1/50 (RVS-027, -028, -031)
- 13 - SOLENOID VALVE - 1/4" LINE, 240VAC/1/50 (RVS-027, -028, -030)
- 14 -
- 15 - TERMINAL BLOCK - (ETE-017, -018, -019, -020, -021, -022)

- 16 -
- 17 - HEATER - 350W @ 230VAC, 1.52A (EHE-053)
- 18 - WATER PAN HEATER - 175W @ 230VAC, 0.76A (EHE-030)
- 19 - POWER SUPPLY - 95-265VAC INPUT, 24VDC, (ETR-039)
- 20 - HUMIDITY SENSOR - 0-1VDC OUTPUT (EHU-073)
- 21 - TERMINAL BLOCK - 16 TERMINALS, 4 SET (ETE-030)
- 22 -
- 23 - PLUG - CORDSET, 3-WIRE, AWG 18, 300V, (EPL-006)
- 24 - RECEPTACLE - CORDSET, 3-WIRE, AWG 18, 300V (ERE-014)
- 25 -
- 26 - FLOAT SWITCH - GEMS MODEL LS-3, NO (EFS-001)
- 27 - QUENCH ARC - 100 OHMS, 0.1 MFD (RRC-028)
- 28 - WATER SUPPLY S.V. - 220VAC/1/ 50Hz (RVS-020)
- 29 - POWER SUPPLY - 95-265VAC INPUT, 12VDC, (ETR-036)
- 30 -

- 31 - CABLE - USB, FEMALE-MALE, 3ft, BLK (EPC-032)
- 32 -
- 33 -
- 34 -
- 35 -
- 36 - TOUCHSCREEN - 10", SIBO, 12VDC/1500mA, 18W (EPC-044)
- 37 - ETHERNET CABLE - 3FT, MALE-MALE, BLK (EPC-052)
- 38 - CIRCUIT BREAKER - 1-POLE, 2A (EBR-147)
- 39 - CIRCUIT BREAKER - 1-POLE, 3A (EBR-163)
- 40 -
- 41 -
- 42 -
- 43 - CIRCUIT BREAKER - 1-POLE, 10A (EBR-145)
- 44 - CIRCUIT BREAKER - 1-POLE, 20A (EBR-169)
- 45 -

ELECTRICAL SYSTEM CHARACTERISTICS		
VOLTAGE: 230 VAC	PHASE: 1Ø	FREQUENCY: 50 Hz
AMPERAGE DRAW (MAX)		
MODEL #	CORD #1	RLA / MCA
E-41L2	12.1A	12.1A/15.1A

PERCIVAL SCIENTIFIC, INC.		
TITLE: ELECTRICAL SCHEMATIC - GENERAL		
MODEL: E-41L2	DATE: 10/7/2020	DRAWING: 029140-1-0-1
BY: LNB		